

03/15/99

JC595 U.S. PTO

**UTILITY PATENT  
APPLICATION TRANSMITTAL**(Only for new nonprovisional applications  
under 37 CFR 1.53(b))

Attorney Docket No.

990264

Total Pages

First Named Inventor or Application Identifier

Masahiro SHIOJI and Toru ASAEDA

Express Mail Label No.

Check Box, if applicable [ ] Duplicate

APPLICATION ELEMENTS FOR:

**DIGITAL CAMERA CAPABLE OF IMAGE  
PROCESSING**ADDRESS TO: Assistant Commissioner for Patents  
BOX PATENT APPLICATIONS  
Washington, D.C. 20231

1. ☒ Fee Transmittal Form (Incorporated within this form)  
(Submit an original and a duplicate for fee processing)
2. ☒ Specification Total Pages [35]
3. ☒ Drawing(s) (35 USC 113) Total Sheets [21]
4. ☒ Oath or Declaration Total Pages [2]
  - a. ☒ Newly executed (original)
  - b. ☐ Copy from prior application (37 CFR 1.63(d)  
(for continuation/divisional with Box 17 completed).
    - i. ☐ Deletion of Inventor(s)  
Signed statement attached deleting inventor(s) named in prior application,  
see 37 CFR 1.63(d)(2) and 1.33(b).
5. ☐ Incorporation by reference (useable if box 4b is checked)  
The entire disclosure of the prior application, from which a copy of the oath or declaration is supplied under  
Box 4b, is considered as being part of the disclosure of the accompanying application and is hereby  
incorporated by reference therein.
6. ☐ Microfiche Computer Program (Appendix)
7. ☐ Nucleotide and/or Amino Acid Sequence Submission (if applicable, all necessary)
  - a. ☐ Computer Readable Copy
  - b. ☐ Paper Copy (identical to computer copy)
  - c. ☐ Statement Verifying identity of above copies

**ACCOMPANYING APPLICATION PARTS**

8. ☒ Assignment Papers (cover sheet and document(s))
9. ☐ 37 CFR 3.73(b) Statement (when there is an assignee) ☒ Power of Attorney

# UTILITY PATENT APPLICATION TRANSMITTAL

(Only for new nonprovisional applications  
under 37 CFR 1.53(b))

Attorney Docket No.

990264

First Named Inventor or Application Identifier

Masahiro SHIOJI and Toru ASAEDA

PAGE 2 OF 3

10. ☐ English translation Document (if applicable)

11. ☒ Information Disclosure Statement ☒ Copies of IDS Citations (PTO-1449 w/1 ref.)

12. ☐ Preliminary Amendment

13. ☒ Return Receipt Postcard (MPEP 503)

14. ☐ Small Entity Statement(s) ☐ Statement filed in prior application  
Status still proper and desired.

15. ☒ Claim for Convention Priority ☒ Certified copy of Priority Document(s)

a. Priority of \_\_\_\_\_ application no. \_\_\_\_\_ filed on \_\_\_\_\_ is claimed under 35 USC 119.  
The certified copies/copy have/has been filed in prior application Serial No. \_\_\_\_\_.  
(For Continuing Applications, if applicable).

16. ☐ Other \_\_\_\_\_

17. If a CONTINUING APPLICATION, check appropriate box and supply the requisite information:

☐ Continuation ☐ Division ☐ Continuation-in-part (CIP) of prior application no. \_\_\_\_/\_\_\_\_

FEE TRANSMITTAL	Number Filed	Number Extra	Rate	Basic Fee
The filing fee is calculated below				\$760.00
Total Claims	22 - 20	2	x \$18.00	36.00
Independent Claims	3 - 3		x \$78.00	
Multiple Dependent Claims			\$260.00	
Basic Filing Fee				796.00
Reduction by 1/2 for small entity				
Fee for recording enclosed Assignment			\$40.00	40.00
TOTAL				\$836.00

**UTILITY PATENT  
APPLICATION TRANSMITTAL**

(Only for new nonprovisional applications  
under 37 CFR 1.53(b))

Attorney Docket No.

**990264**

First Named Inventor or Application Identifier

**Masahiro SHIOJI and Toru ASAEDA**

**PAGE 3 OF 3**

☒ A check in the amount of \$836.00 is enclosed to cover the filing fee of \$796.00 and the assignment recordation fee of \$40.00.

☐ Please charge our Deposit Account No. **01-2340** in the total amount of \_\_\_\_\_ to cover the filing fee and the \_\_\_\_\_ assignment recordation fee. A duplicate of this sheet is attached.

☒ The Commissioner is hereby authorized to charge payment for any additional filing fees required under 37 CFR 1.16 or credit any overpayment to Deposit Account No. **01-2340**. A duplicate of this sheet is attached.


**18. CORRESPONDENCE ADDRESS**

**ARMSTRONG, WESTERMAN, HATTORI  
McLELAND & NAUGHTON  
1725 K Street, N.W. Suite 1000  
Washington, D.C. 20006  
Telephone: (202) 659-2930  
Facsimile: (202) 887-0357**

**SUBMITTED BY**

Typed or Printed Name **William F. Westerman**

Reg. No. **29,988**

Signature 

Date: **March 15, 1999**

WFW/yap

## TITLE OF THE INVENTION

Digital Camera Capable of Image Processing

## BACKGROUND OF THE INVENTION

### Field of the Invention

5           The present invention relates to a digital camera and, more specifically, to a digital camera in which a picked up motion image or a reproduced still image is displayed on a monitor.

### Description of the Background Art

10           In a conventional digital camera of this type, an image recorded on a recording medium is reproduced and displayed on a built in monitor.

          The prior art digital camera, however, is capable of simple reproduction of the recorded image, and in order to process the recorded image, a separate image processing apparatus has been necessary.

## SUMMARY OF THE INVENTION

15           Therefore, an object of the present invention is to provide a digital camera capable of image processing without the necessity of preparing a separate image processing apparatus.

          According to an aspect, the present invention includes an image pickup section for picking up an image of an object, a first forming section responsive to a motion image frame forming instruction of an operator for forming a motion image frame smaller than a monitor frame on a monitor, and a motion image display section for displaying the motion image of the object picked up by the image pickup section on the motion image frame.

20           Therefore, a motion image is displayed on a desired frame formed on the monitor in accordance with the frame forming instruction by the operator, and hence a processed image can be obtained without the necessity of preparing a separate image processing apparatus.

          According to another aspect, the present invention provides a digital camera in which a first still image corresponding to the monitor frame is reproduced from a recording medium and displayed on the monitor, which includes a second still image reproducing section responsive to a synthesization instruction from the operator for reproducing a second still image smaller than the monitor frame from the recording medium, and a

synthesizing section for synthesizing the second and the first still images.

Therefore, the second still image smaller than the monitor frame is synthesized with the first still image in response to the synthesization instruction by the operator, and therefore a processed image can be  
5 obtained without the necessity of preparing the image processing apparatus.

According to a still further aspect, the present invention includes a setting section for setting a through image display area (an image of the object seen through) at a portion of the displayed reproduced image, an image synthesizing section for generating a synthesized image by  
10 displaying the through image on the set area, and a recording section for recording the generated synthesized image. Therefore, the reproduced image and the through image can be synthesized in a simple manner by a digital camera by itself, and a processed image can be obtained without the necessity of preparing an image processing apparatus.

15 The foregoing and other objects, features, aspects and advantages of the present invention will become more apparent from the following detailed description of the present invention when taken in conjunction with the accompanying drawings.

#### BRIEF DESCRIPTION OF THE DRAWINGS

20 Figs. 1A and 1B are perspective views showing appearance of the digital camera in accordance with a first embodiment of the present invention.

Fig. 2 is a block diagram showing configuration of an image recording and reproducing circuit contained in the digital camera shown in  
25 Figs. 1A and 1B.

Figs. 3A and 3B are illustrations representing image pickup modes of the digital camera shown in Figs. 1A and 1B.

Figs. 4A and 4B are illustrations representing the reproduction mode of the digital camera shown in Figs. 1A and 1B.

30 Figs. 5A to 5D are illustrations representing the image synthesizing function of the digital camera shown in Figs. 1A and 1B.

Figs. 6A to 6F represent a modification of the first embodiment.

Fig. 7 is a block diagram representing a configuration of an image

recording and reproducing circuit contained in the digital camera in accordance with a second embodiment of the present invention.

Fig. 8 is a block diagram showing a configuration of a zoom circuit shown in Fig. 7.

5        Fig. 9 is a block diagram showing a configuration of a memory control circuit shown in Fig. 7.

Fig. 10 is a block diagram showing a configuration of an address calculating section shown in Fig. 9.

10       Fig. 11 is a flow chart representing part of an operation in a camera mode.

Fig. 12 is a flow chart showing another part of the operation in the camera mode.

Fig. 13 is a flow chart showing a still further part of the operation in the camera mode.

15       Fig. 14 is a flow chart showing a part of an operation in a reproduction mode.

Fig. 15 is a flow chart showing another part of the operation in the reproduction mode.

20       Fig. 16 is a flow chart showing a further part of the operation in the reproduction mode.

Fig. 17 is a flow chart showing a still further part of the operation in the reproduction mode.

Fig. 18 is a flow chart showing a still further part of the operation in the reproduction mode.

25       Fig. 19 is a flow chart showing a part of an operation in a motion image reducing mode.

Figs. 20A to 20F are illustrations representing an exemplary operation in the motion image reducing mode.

30       Figs. 21A to 21F are illustrations representing another exemplary operation in the motion image reducing mode.

Figs. 22A to 22E are illustrations representing an exemplary operation of a still image cutting mode.

Figs. 23A to 23D are illustrations representing an exemplary

operation in a still image pasting mode.

## DESCRIPTION OF THE PREFERRED EMBODIMENTS

### First Embodiment

Fig. 1A is a perspective view taken from the front side (from the side of the lens) and Fig. 1B is a perspective view taken from the rear side, showing the appearance of the digital camera in accordance with the first embodiment of the present invention.

Referring to Figs. 1A and 1B, on the front side of the digital camera, there are provided a lens 1, a lens cover 2 linked to a power switch, an optical finder 3, a flashlight 4 and an LED (Light Emitting Diode) 5 for a self timer, and on the upper and side surfaces, there are a shutter button 6, a three point type main switch 7, a macro switch lever 8 and a terminal 9. On the rear surface of the digital camera, there are provided an LCD (Liquid Crystal Display) 10, a mode button 11, a set button 12, a direction designating button 13 and a microphone 14.

Main switch 7 is used for switching among three modes, that is, an image pickup mode with LCD 10 on, an image pickup mode with LCD 10 off, and a reproduction mode. In the image pickup mode with LCD 10 on, a through image is displayed on LCD 10 and the through image is recorded. In the image pickup mode with LCD 10 off, image is picked up using optical finder 3 in the similar manner as the conventional camera using silver film. In the reproduction mode, LCD 10 is turned on and a reproduced image is displayed on LCD 10. On LCD 10, in addition to the through image and the reproduced image, various icons (characters) representing recording condition, reproduction function and so on are also displayed.

By pressing lightly each of left, right, up and down direction designating sections 13a, 13b, 13c and 13d of direction designating button 13, feeding/reversing of the reproduced image, setting of recording condition, selection of reproduction function and so on can be set.

Fig. 2 is a block diagram representing a configuration of an image recording and reproducing circuit 20 contained in the digital camera.

Referring to Fig. 2, in image recording and reproducing circuit 20, a system controller 41 applies various control signals to a CPU (Central

Processing Unit) 42 at prescribed timings, in response to signals from lens cover 2, shutter button 6, main switch 7, macro switch lever 8, mode button 11, set button 12 and direction designating button 13. In accordance with the control signals applied from system controller 41, CPU 42 controls a

5 memory control circuit 27 and a flash memory control circuit 47.

Memory control circuit 27 controls a first signal processing circuit 24, a second signal processing circuit 29, a JPEG (Joint Photographic Expert Group) circuit 44, buffers 25, 28, 43 and an SDRAM (Synchronous Dynamic random Access Memory) 26. Write/read of image data to and from

10 SDRAM 26 are performed through buffers 25, 28 and 43. As the speed of transfer between buffers 25, 28 and 43 and SDRAM 26 (write/read) is made faster than the speed of data transfer among buffers 25, 28, 43, the first signal processing circuit 24, the second signal processing circuit 29 and JPEG circuit 44, the circuit 24, 29 and 44 can operate almost

15 simultaneously.

Memory control circuit 27 controls a character generator 30 and a switch 31 so that a part of image data is replaced with a character image data, whereby a character image is overwritten on the through image or the reproduced image.

Flash memory control circuit 47 controls buffer 45 and flash memory 46, writes image data compressed by JPEG circuit 44 to flash memory 46 through buffer 45, and applies data read from flash memory 46 to JPEG circuit 44 through buffer 45.

20

In the image pickup mode, an optical image entering through lens 1 is incident on a CCD (Charge Coupled Device) imager 21 through a complementary color filter, not shown. CCD imager 21 outputs electric signals (progressive scan signals) of pixels in accordance with progressive scanning (progressive scanning of pixels). The progressive scan signals from CCD imager 21 is applied to a CDS/AGC (Correlate Double Sampling/

25 Auto Gain Control) circuit 22.

30

CDS/AGC circuit performs known noise removal and level adjustment on the progressive scan signals, and the progressive scan signals which have been subjected to such processings are converted to



digital data (image data) by A/D converter 23. First signal processing circuit 24 performs known white balance adjustment and gamma correction on the image data output from A/D converter 23, and thereafter, applies the image data to SDRAM 26 through buffer 25.

5 Memory control circuit 27 writes the image data to SDRAM 26, and thereafter reads the image data by interlace scanning. Therefore, odd-numbered field image data and even-numbered field image data are output alternately from SDRAM 26. The image data output from SDRAM 26 are input to second signal processing circuit 29 through buffer 28 and to JPG circuit 44 through buffer 43.

10 The second signal processing circuit 29 performs processing such as color interpolation on the input image data, and image data output from second signal processing circuit 29 are applied to D/A converter 32 through switch 31. D/A converter 32 converts the image data to analog signals (image signals), which image signals are output through an output terminal 33 and applied to LCD 10. Therefore, real time motion image (through image) 50 is displayed on LCD 10, as shown in Fig. 3A.

When mode button 11 is pressed in this state, various icons 51 to 59 indicating the recording condition are displayed on an end portion of LCD 10. In Fig. 3B, the icons are represented as a simple white rectangle and hatched rectangles, for simplicity of the drawing. Actually, the icons are marks representing corresponding recording conditions. Icons 51 to 59 are for setting a still image pickup mode, high speed continuous image pickup mode, resolution, voice memo, self timer, macro mode display, exposure correction and digital zooming. Icons 51 to 59 are selected by direction designating button 13. Among icons 51 to 59, the selected icon (in the figure, icon 51) is displayed in a positive state (white rectangle) and other icons are displayed in a negative state (hatched rectangles). When set button 12 is pressed in this state, the condition represented by the selected icon (in this case, icon 51) is set (in this case, still image pickup mode). When mode button 11 is pressed after the setting of recording conditions, icons 51 to 59 disappear and the display returns to the state of Fig. 3A.

When an operator presses a shutter button 6, JPEG circuit 44 is

activated, image data read from SDRAM 26 and input to JPEG circuit 44 through buffer 43 are compressed in accordance with a JPEG format, and the compressed data is written to flash memory 46 through buffer 45. In a reproduction mode, the compressed data read from flash memory 46 is  
5 input to JPEG circuit 44 through buffer 45. JPEG circuit 44 decompresses the input compressed data and applies the data to SDRAM 26 through buffer 43. Memory control circuit 27 writes the image data to SDRAM 26, and thereafter, read the image data by interlace scanning.

The image data read from SDRAM 26 are applied through buffer 28,  
10 second signal processing circuit 29 and switch 31 to D/A converter 32 and converted to analog image signals. The analog image signals are output to the outside through output terminal 33 and to LCD 10. Thus as shown in Fig. 4A, reproduced image 60 is displayed on LCD 10. When left direction designating section 13a of direction designating button 13 is pressed, an  
15 image recorded prior to the reproduced image is reproduced, and when the right direction designating section 13b is pressed, an image recorded after the reproduced image is reproduced. In this manner, a desired image can be selected and reproduced.

When mode button 11 is pressed in this state, various icons 61 to 68  
20 representing reproducing functions are displayed on an end portion of LCD 10 as shown in Fig. 4B. Icons 61 to 68 are for selecting reproduction mode, multireproduction, reproduction zooming, protection, erasure, image synthesization, card operation and setting of date and time, respectively. A desired one of icons 61 to 68 is selected by direction designating button  
25 13 and when set button 12 is pressed, the function represented by the icon is selected. When mode button 11 is pressed without pressing set button 12, the display returns to the state of Fig. 4A.

The image synthesizing function, which is the feature of the present invention, will be described. First, in the state shown in Fig. 4A, direction  
30 designating button 13 is used to feed/reverse the reproduced image, and a desired reproduced image 60 as a background is selected. Thereafter, mode button 11 is pressed so that icons 61 to 68 are displayed as shown in Fig. 4B, icon 66 for image synthesization is selected by using direction

designating button 13, and set button 12 is pressed.

5 In this manner, image synthesizing function is selected, and a vertical line L1 and a horizontal line L2 are displayed on reproduced image 60 as shown in Fig. 5A. When the left direction designating section 13A or the right direction designation section 13b of direction designating button 13 is pressed, the vertical line L1 moves to the left or the right, and when the upper direction designating section 13c or the lower direction designating section 13d is pressed, the horizontal line L2 moves upward or downward. By moving the vertical line L1 and the horizontal line L2, position of a first point P1 which is an intersecting point of these lines is determined. The first point P1 is an upper left point of a frame F.

10 When set button 12 is pressed in this state, the first point P1 is determined as shown in Fig. 5B, and a vertical line L3 and a horizontal line L4 are further displayed on reproduced image 60. When the left direction designating section 13a or the right direction designating section 13b of direction designating button 13 is pressed, the vertical line L3 moves to the left or to the right, and when the upper direction designating section 13c or the lower direction designating section 13d is pressed, the horizontal line L4 moves upward or downward. The vertical line L3 and the horizontal line L4 are movable on the lower side and to the right of the first point P1. When one of the vertical line L3 and the horizontal line L4 is moved, the other of the vertical line L3 and the horizontal line L4 follows such that the aspect ratio of the frame F having L1 to L4 as its four sides is always kept at 3:4. By moving vertical line L3 and horizontal line L4, the position of the second point P2 which is an intersection of these lines is determined. The second point B2 is the lower right point of frame F.

20 When set button 12 is pressed in this state, the size and approximate position of frame F is determined as shown in Fig. 5C. When the direction designating section 13a to 13d of direction designating button 13 is pressed, the frame F moves in the designated direction. By moving the frame F, the position of the frame F is determined.

30 When set button 12 is pressed in this state, a through image 50 is displayed in an area surrounded by the frame F, as shown in Fig. 5D. At

this time, in the circuit 20 shown in Fig. 2, the through image data generated by A/D converter 23 is thinned out, that is, subjected to a so called reduction zooming, by the first signal processing circuit 24 conforming to the size and position of the frame F. The thinned out  
5 through image data are applied to SDRAM 26 through buffer 25, and overwritten on that area of the reproduced still image data written in SDRAM 26 which corresponds to the area surrounded by the frame F. As the through image is a motion image, the overwriting data is successively updated. In this manner, a window of a desired size and position is  
10 opened in the reproduced image 60, and through image 50 is displayed on the window.

When shutter button 6 is pressed in this state, the image data of the synthesized image displayed on the LCD 10 at that time are compressed by JPEG circuit 44 and written to flash memory 46 through buffer 45.  
15 Therefore, it becomes possible to reproduce the synthesized image in the similar manner as the still image picked up in the normal image pickup mode.

When mode button 11 is pressed in the state represented by Figs. 5A to 5D, the display returns to the state of Fig. 5A, and when mode button 11  
20 is pressed again in this state, the display returns to the state of Fig. 3B.

In the present embodiment, the thinned out through image data are overwritten on the reproduced image data at the time of image synthesization to produce a synthesized image. However, the embodiment is not limited thereto. For example, all the through image data and the  
25 reproduced image data may be separately written to memory areas of SDRAM 26, the reproduced image data may be read outside the frame F and the through the image data may be read inside the frame F, to produce the synthesized image.

Further, the vertical line L3 and the horizontal line L4 are moved  
30 with the aspect ratio of the frame F having L1 to L4 as four sides is always kept at 3:4 in the above described embodiment. However, the ratio is not limited, and the position of the second point P2 may be set regardless of the ratio of 3:4.

Figs. 6A to 6F represent a modification of the first embodiment.

Fig. 6A shows a reproduced image displayed on LCD 10, and Fig. 6B shows the through image. In the embodiment described above, when set button 12 is pressed after the position of frame F is determined, through image 50 which has been thinned out and reduced in size is displayed in the area surrounded by frame F as shown in Fig. 6D.

By contrast, in this modification, when set button 12 is pressed continuously, only a part of the through image corresponding to the frame extracted from the whole image is displayed as shown in Fig. 6C, without thinning out as shown in Fig. 6D.

Further, when the position of the first point P1 is determined by moving the vertical line L1 and the horizontal line L2, the color of the vertical and horizontal lines L1 and L2 may be changed from white to orange, for example, and when the aspect ratio of frame F is set at 3:4 by moving the vertical line L3 and the horizontal line L4, the color of the vertical and horizontal lines L3 and L4, represented by the double lines in Fig. 6E, may be changed from white to green, for example, as represented by a thick black line in Fig. 6F.

#### Second Embodiment

In the present embodiment, when a motion image reducing mode is set, a pointer is displayed on the monitor. When the operator operates a cursor key, the pointer moves, and when the operator operates a determination key at two different pointer positions, a rectangular frame is formed. More specifically, the two pointer positions present the upper left and lower right coordinates of the frame. The picked up real time motion image is displayed in the rectangular frame. The displayed motion image is reduced to a magnification corresponding to the ratio of the rectangular frame with respect to the monitor frame. In the portion of the monitor frame outside the rectangular frame, a still image reproduced from the recording medium may be displayed. When the operator operates the shutter button in this state, the image in the monitor frame is recorded on the recording medium.

Further, when a still image paste mode is set with the reproduced

still image being displayed on the monitor, a partial still image recorded separately is synthesized with the still image which is displayed originally. When the cursor key is operated in the upward/downward direction, display of the partial still image is switched, and when the cursor key is operated in the left/write direction, the still image displayed below the partial image is switched. When the shutter button is operated, the synthesized image which is being displayed is recorded on the recording medium.

This embodiment will be described in detail with reference to the figures.

Referring to Fig. 7, the digital camera 70 in accordance with the present embodiment includes a lens 71. An incident optical image of the object enters CCD imager 72 through lens 71. CCD imager 72 has 640 pixels and 480 lines of pixels in the horizontal and vertical directions.

When a mode setting switch 87 is set to the side of the camera, a system controller 85 sets camera mode in CPU 83 through an interruption terminal 83. At this time, CPU 83 designates reading of pixel signals (camera signals) to timing generator 84, and timing generator 84 reads camera signals in raster scan method, from CCD imager 72. The read camera signals are converted to digital signals (camera data) by an A/D converter 73, and the converted camera data are input to a signal processing circuit 74. In front of CCD imager 72, a complementary color filter, not shown, is attached, and pixels of the input camera data each has only one complementary color component of Ye, Cy, Mg or G. Therefore, signal processing circuit 74 performs color separation on the input camera data, and RGB data obtained through color separation are subjected to YUV conversion.

The YUV data obtained in this manner, that is, the image data is subjected to a prescribed zooming process by a zoom circuit 75, input to DRAM 81 through a bus 76 and written to a video memory area 81a in accordance with raster scan method. Video area 81a has a capacity corresponding to a frame of monitor 80 (monitor frame), and image data output from zoom circuit 75 are written to the video memory area 81 by

DMA (Direct Memory Access). More specifically, CPU 83 applies, together with a write request, the frame data, that is, the X and Y coordinates at the upper left corner of the frame as well as the data of horizontal and vertical sizes (X size and Y size) to memory control circuit 78, and in accordance  
5 with the frame data, memory control circuit 78 writes the image data at a prescribed position of video memory area 81a. In the normal camera mode, frame data of the monitor frame are input to memory control circuit 78. The upper left coordinates of the monitor frame are (0, 0), and the horizontal and vertical sizes are 640 pixels and 480 lines, respectively.  
10 Therefore, image data are written in the full video memory area 81a.

After the completion of writing, the image data of video memory area 81a are read in accordance with the raster scan method by memory control circuit 78, and applied to a video encoder 79 through a bus 76. Video encoder 79 encodes the input image data in accordance with NTSC method,  
15 and the resulting composite video signals are output to monitor 80 which also serves as a view finder. The motion picture picked up by CCD imager 72 is displayed fully on the monitor frame. A buffer, not shown, is provided at an input/output port of DRAM 81, and transfer rate of the image data is converted. Therefore, writing and reading of image data can  
20 be executed in parallel.

When the operator operates the shutter button 89 in the normal camera mode, CPU 83 instructs timing generator 84 to stop reading of charges. Thus new reading of image data from CCD imager 72 is stopped, and image data at the time point when shutter button 89 is pressed is kept  
25 maintained in video memory area 81. CPU 83 reads the image data from video memory area 81a by DMA, and inputs the data to a compression/decompression circuit 77 through a bus 76. At the same time, CPU 83 applies a compression instruction to compression/decompression circuit 77. Compression/decompression circuit 77 compresses the input  
30 image data in accordance with the JPEG method, stores the compressed image data in an image file, and applies the image file to a memory card 82. To memory card 82, a write instruction is also applied from CPU 83, and the image file output from compression/decompression circuit 87 is recorded

on memory card 82.

When the operator sets the mode setting switch 87 to the reproducing side, system controller 85 sets CPU 83 in the reproduction mode. In response, CPU 83 reproduces a desired image file from memory card 82, and applies the image file to compression/decompression circuit 77 through bus 76. A decompression instruction from CPU 83 is also applied to compression/decompression circuit 77. Compression/decompression circuit 77 decompresses the image data of the input image file in accordance with the JPEG method, and inputs the decompressed image data, that is, the reproduced image data to DRAM 81. In order to write the reproduced image data to video memory area 81a, a write request is applied from compression/decompression circuit 77 to memory control circuit 78, and frame data defining the position of writing is applied from CPU 83 to memory control circuit 78.

In accordance with the write request and the frame data, memory control circuit 78 writes the reproduced image data to video memory area 81a. When writing is completed, CPU 83 inputs the same frame data and a read request to memory control circuit 78 and, in response, memory control circuit 78 reads the reproduced image data from video memory area 81a. The read reproduced image data is applied to video encoder 79 and, finally, the reproduced still image is displayed on monitor 80.

Zoom circuit 75 is configured as shown in Fig. 8. Image data output from signal processing circuit 74 is written to a line memory 75a in response to a pixel clock and thereafter read, delayed by one line by the same pixel clock. The read image data is again written to another line memory 75b and read delayed by one line. Therefore, from line memories 75a and 75b, image data of continuous two lines are output simultaneously. The image data output from line memory 75a is directly input to a multiplier 75g and in addition, input to a multiplier 75f delayed by one pixel by latch circuit 75c. Image data output from line memory 75b is directly input to multiplier 75i and input to multiplier 75h delayed by one pixel by latch circuit 75d.

To multipliers 75g and 75i, a decimal of the numerical value data



output from an adder 75y is input, and to multipliers 75f and 75h, a complement obtained by subtracting the decimal from "1.0" by a subtracter 75e is input. Therefore, the image data applied to multipliers 75g and 75i are weighted by the decimal while the image data applied to multipliers 75f and 75h are weighted by the complement. Outputs of multipliers 75f and 75g are added by an adder 75j, while outputs of multipliers 75h and 75i are added by an adder 75k. By such multiplexing and adding operations, the image data are subjected to horizontal zooming.

The added data output from adders 75j and 75k are input to multipliers 75n and 75p. A decimal of the numerical value data output from adder 75z is input to a multiplier 75p, and a complement obtained by subtracting the decimal from "1.0" by a subtracter 75m is input to a multiplier 75n. Thus the added data output from adder 75j is multiplied by the complement, while the added data output from adder 75k is multiplied by the decimal. Thereafter, the outputs from multipliers 75n and 75p are added by an adder 75q, whereby image data subjected to zooming both in the horizontal and vertical directions are obtained.

The numerical value data output from adders 75y and 75z are calculated in the following manner. CPU 83 inputs X size data and Y size data included in the frame data to an H counter 75r and a V counter 75s, respectively. Thus the X size is the maximum count value of H counter 75r, and Y size is the maximum count number of V counter 75s. H counter 75r is incremented by the output of an AND circuit 75x, outputs a carry signal at the maximum count value, and is reset by a horizontal synchronizing signal and a vertical synchronizing signal. V counter 75s is incremented by the carry signal output from H counter 75r and reset by the vertical synchronizing signal. An output from AND circuit 75x is a clock which rises at the timing of each pixel constituting the zoom image, that is, a zoom pixel clock. Based on the zoom pixel clock, the horizontal pixel number and the vertical pixel number of the zoom image are counted by the H and V counters 75r and 75s.

A divider 75t divides the count value of H counter 75r by a horizontal zoom magnification output from CPU 83, and a divider 75u divides the

count value of V counter 75s by the vertical zoom magnification output from CPU 83. The result of division by divider 75t is added to X coordinate data included in the frame data by adder 75y, whereas the result of division by divider 75u is added to Y coordinate data included in the frame data by adder 75j. The results of adders 75y and 75z represent which horizontal position and which vertical position of the original image the zoom pixel output from adder 75q at present correspond to. The horizontal position data and vertical position data of the original image are output from adders 75y and 75z, the decimal of the horizontal position data is input to subtracter 75e, multipliers 75g and 75i and the decimal of the vertical position data is input to subtracter 75m and multiplier 75p.

Integers of the horizontal and vertical position data output from adders 75y and 75z are input to comparators 75v and 75w. A horizontal count value which represents the count of horizontal pixel number of the original image is input to comparator 75v, and a vertical count value representing the count of vertical pixel number of the original image is input to comparator 75w. Comparators 75v and 75w output a match pulse when input to numerical values match each other. AND circuit 75x provides logical product of match pulses output from comparators 75b and 75w and outputs a logical product signal (AND signal) as a zoom pixel clock. The zoom pixel clock is input to memory control circuit 78, and memory control circuit 78 writes only the pixel data output from adder 75q simultaneously with zoom pixel clock to DRAM 81. Thus image data of a desired zoom magnification is obtained in the DRAM 81. Here, the original image refers to an image of the object entering the CCD imager 72, and the original image data is obtained from signal processing circuit 74.

Memory control circuit 78 is configured as shown in Fig. 9. X size data and Y size data included in the frame data are loaded to decoders 93 and 94, respectively, and X coordinate data and Y coordinate data are loaded to an address operating circuit 95. Address operating circuit 95 is configured as shown in Fig. 10, and X coordinate data and Y coordinate data are loaded to registers 105 and 106, more specifically. In the normal camera mode, decoders 93 and 94 hold numerical value data of "640" and

"480", and registers 105 and 106 both hold numerical value data of "0".  
The numerical value data held in registers 105 and 106 are updated at the  
input timing of vertical synchronizing pulse  $V_{sync}$ .

5        An H counter 91 is incremented by the zoom pixel clock input from  
zoom circuit 75, and count value of H counter 91 (horizontal count value) is  
input to address operating circuit 95 and decoder 93. Decoder 93  
compares the input horizontal count value with "640", and when these  
match each other, outputs a match pulse. H counter 91 is reset by the  
match pulse, and V counter 92 is incremented by the match pulse. The  
10       counter value of V counter 92 (vertical count value) is applied to address  
operating circuit 95 and decoder 94, and decoder 94 resets V counter 92  
when the vertical count value matches "480". In this manner, H counter  
91 is reset when pixels corresponding to the X size of the frame is counted,  
and V counter 92 is reset when lines corresponding to the Y size of the  
15       frame is counted.

Referring to Fig. 10, the horizontal and vertical count values are  
applied to adders 101 and 102 provided in address operating circuit 95.  
Adder 101 adds the horizontal count value to the X coordinate data held in  
register 105, while adder 102 adds the vertical count value to Y coordinate  
20       data held in register 106. The result of addition of adder 102 is thereafter  
applied to a multiplier 103 and multiplier 103 multiplies the input result of  
addition by the numerical value data "640" held in register 107. Adder  
104 adds the result of addition by adder 101 to the result of multiplication  
by multiplier 103. More specifically, address operating circuit 95  
25       generates an address signal by an operation represented by the following  
equation (1).

$$\text{Address} = (\text{Horizontal Count Value} + \text{Upper Left X Coordinate}) + \\ (\text{Vertical Count Value} + \text{Left Y Coordinate}) \times 640 \dots (1)$$

30

Controller 96 receives the address signal from address operating  
circuit 95 and a write/read request from CPU 83 or  
compression/decompression circuit 77, and outputs an address signal, W/R

signal and an enable signal to DRAM 81. More specifically, controller 96 outputs the address signal from address operating circuit 95 as it is, and sets the enable signal to the high level at the same time. When a write request is applied, the controller sets the W/R signal to the high level, and  
5 when a read request is applied, sets the W/R signal to the low level. By such address signal, W/R signal and enable signal, an access to the desired address of video memory area 81a is performed. Memory control circuit 78 operates in the above described manner based on the frame data from CPU 83, and forms a desired frame on video memory area 81a, and therefore, on  
10 monitor 80.

CPU 83 performs the processing represented by the flow chart of Figs. 11 to 13 when the mode setting switch 87 is set to the side of the camera, and performs the process represented by the flow chart of Figs. 14 to 18 when the mode setting switch 87 is set to the reproducing side. Further,  
15 CPU 83 processes the subroutine represented by Fig. 19, as needed.

When the camera mode is set, CPU 83 initializes horizontal zoom magnification, vertical zoom magnification and frame data in step S1 of Fig. 11. At this time, zoom magnification is set to 1 both in the vertical and horizontal directions. As to the frame size, X and Y sizes are set to "640" and "480", and X and Y coordinates are both set to "0". Therefore, from  
20 zoom circuit 75, the picked up image data is output with the zoom magnification of 1, and an instruction is given to memory control circuit 78 so that a motion picture frame corresponding to the monitor frame is formed. CPU 83 instructs timing generator 84 to read charges in step S2, that is, enables CCD imager 72 in step S2, and thereafter, in step S3,  
25 outputs a write request to memory control circuit 78 so that image data of one frame are written from zoom circuit 75 to video memory area 81a. As a result, a motion image frame corresponding to the monitor frame is formed on video memory area 81a, and image data are written to the  
30 motion image frame.

In step S5, CPU 83 applies a read request to memory control circuit 78 and reads all image data from video memory area 81a. Consequently, a real time object image is displayed fully on the monitor frame. More

specifically, a motion image frame of the same size as the monitor frame is formed on monitor 80, and the picked up motion image is displayed on the motion image frame. Thereafter, in steps S7 and S9, CPU 83 determines whether a motion image reducing mode is set or not and whether shutter button 89 is pressed or not. If the answer in each step is "NO", the flow returns to step S3. Therefore, unless the operator performs any key operation, the processes of steps S3 and S5 are repeated, and a motion image is continuously displayed on monitor 80.

When the operator operates shutter button 89 with the motion image being output from monitor 80, CPU 83 determines that the answer of step S9 is "YES", and in step S24 of Fig. 13, CPU 83 instructs timing generator 84 to stop reading of charges. Thus CCD imager 72 is disabled, and image data at the time point when shutter button 89 is pressed is maintained in video memory area 81a. Thereafter, CPU 38 reads the image data from video memory area 81a in step S25, applies the data to compression/decompression circuit 77 and performs JPEG compression. In step S25, in addition to reading of image data, a compression instruction is applied to compression/decompression circuit 77, whereby the image data is compressed.

In step S27, whether the present operation mode is the motion image reducing mode or not is determined. If it is "NO", then in steps S30 and S31, an instruction to form a pic file and an instruction to store the compressed image data to the pic file are applied to compression/decompression circuit 77, respectively. In step S31, writing of the size data of the motion image frame to the pic file is also instructed. Therefore, the image data picked up in the normal camera mode are stored in the image file "pic000P.jpg" having an identifier "pic" added thereto (where P is an integer), and the size data of the motion image frame is written to the header portion of the image file. CPU 83 records such a pic file in memory card 82 in step S33, and the flow returns to step S1. In step S33, memory card 82 is instructed to write the image file.

When the operator sets the motion image reducing mode by the operation of a menu, CPU 83 determines it is "YES" in step S7, disables

CCD imager 72 in step S10 of Fig. 12, and performs frame determining process in step S11.

More specifically, referring to Fig. 19, in step S119, pointer data is read from character area 81b of DRAM 81, and the pointer is displayed on monitor 80. Thereafter, in steps S121 and S125, operations of cursor keys 86a to 86d and determination key 88 are monitored, respectively. When any of cursor keys 86a to 86d is operated, CPU 83 determines that it is "YES" in step S121, changes the position of display of the pointer in accordance with the key operation in step S123, and the flow returns to step S119. When determination key 88 is operated, whether flag 83a is set or not is determined in step S127. If flag 83a is not set, CPU 83 determines the present pointer position as an upper left coordinates of the motion image frame in step S129, sets flag 83a in step S131, and the flow returns to step S119.

When it is determined in step S127 that flag 83a is set, CPU 83 determines the present pointer position as the lower right coordinates of the motion image frame in step S133. In step S135, flag 83a is reset, and in step S137, the X and Y sizes of the motion image frame are calculated in accordance with the following equation (2). More specifically, by subtracting the upper left X coordinate from the lower right X coordinate of the motion image frame, the X size is calculated, and by subtracting the upper left Y coordinate from the lower right Y coordinate of the motion image frame, the Y size is calculated.

X size = lower right X coordinate - upper left X coordinate

Y size = lower right Y coordinate - upper left Y coordinate

Upper left X coordinate: X coordinate at an upper left vertex of rectangular frame

Upper left Y coordinate: Y coordinate at the upper left vertex of rectangular frame

Lower right X coordinate: X coordinate at a lower right vertex of rectangular frame

Lower right Y coordinate: Y coordinate at the lower right vertex of

the rectangular frame ... (2)

Returning to Fig. 12, in step S12, zoom magnification of the motion image is calculated in accordance with the following equation (3). The  
5 calculated zoom magnification is set in the zoom circuit 75. More specifically, the Z size of the calculated motion image frame is divided by the X size of the monitor frame to calculate the horizontal zoom magnification, and the Y size of the calculated motion image frame is  
10 divided by the Y size of the monitor frame to calculate the vertical zoom magnification.

Horizontal zoom magnification = X size of the motion image frame/X size of the monitor frame

Vertical zoom magnification = Y size of the motion image frame/Y  
15 size of the monitor frame ... (3)

Thereafter, in step S13, the size data and the upper left coordinate data of the frame obtained in step S11 and the zoom magnification calculated in step S12 are set in zoom circuit 75. In this manner, the data  
20 of reduced image which has been reduced in size to be within the motion image frame are generated.

Thereafter, in step S14, CPU 83 instructs timing generator 84 to read charges, and enables CCD imager 72. In step S15, CPU 83 applies a write request to memory control circuit 78, and data of X and Y sizes and  
25 upper left X and Y coordinates calculated in step S11, that is, frame data of the motion image frame are applied to memory control circuit 78. Accordingly, a desired motion image frame is formed in video memory area 81a, and the reduced image data output from zoom circuit 75 is written to the motion image frame. In step S17, CPU 83 applies a read request and  
30 the initial frame data to memory control circuit 78, and all image data stored in video memory area 81a are read. Accordingly, the reduced motion image and gray image are displayed on monitor 80. More specifically, the reduced motion image is displayed on the motion image

frame formed on monitor 80, and on the portion other than the motion image frame of the monitor frame, gray image is displayed. When the motion is image frame formed by the operator has an aspect ratio different from that of the monitor frame, the reduced motion image displayed is

5 distorted in the horizontal or vertical direction.

CPU 83 monitors operations of cursor keys 86a to 86d and shutter button 89 in steps S19 and S23, and when none of these is operated, repeats the processes of steps S15 and S17. Thus the reduced motion image is displayed in the motion image frame. When any of cursor keys

10 86a to 86d is operated, the image data in video memory area 81a is cleared in step S21, the X and Y coordinates data contained in the frame data, that is, the upper left coordinate data of the motion image frame are updated, and thereafter the flow returns to step S15. In this manner, the write position of reduced image data is changed, and as a result, the motion

15 image frame displayed on monitor 80 moves.

When shutter button 89 is operated, CPU 83 disables CCD imager 72 in step S24, and performs JPEG compression on the reduced image data at the time when the shutter button 89 is pressed, in step S25. At this time, CPU 83 applies a read request and the frame data of the motion image

20 frame to memory control circuit 78, and instructs compression/decompression circuit 77 to perform JPEG compression. Therefore, only the image data within the motion image frame are compressed. In step S27, whether the present operation mode is the motion image reducing mode or not is determined and if it is "YES", then

25 instruction to form an image file "syn000S.jpg" (where S is an integer) with an identifier "syn" is applied to compression/decompression circuit 77 in step S28, and an instruction to store the compressed image data to syn file and to write the size data of the motion image frame to the syn file is applied to compression/decompression circuit 77 in step S29. Accordingly,

30 the image data of a frame smaller than the monitor frame is stored in the syn file, and size data of the motion image frame is written to the header portion of the syn file. CPU 83 stores the syn file storing the image data in this manner in memory card 82 in step S33, and the flow returns to step



S1.

When the camera mode is set, a motion image of the object is displayed on monitor 80 as shown in Fig. 20A, for example. When the operator sets the motion image reducing mode here, display of the object disappears as shown in Fig. 20B, and, instead, a cross shaped pointer is displayed on monitor 80. The pointer moves on the screen in accordance with the operation of cursor keys 86a to 86d. When the operator operates the determination key 88 at the pointer position shown in Fig. 20B, the pointer position serves as the upper left coordinates of the motion image frame. After the upper left coordinates are determined, display of the pointer continuous, and the pointer moves on the screen in accordance with the operation of cursor keys 86a to 86d. When the operator moves the pointer to a position represented in Fig. 20C and presses determination key 88, the pointer position will be the lower right coordinates of the motion image frame. In this manner, the position and the size of the motion image frame are determined. Then, the motion image frame is formed on monitor 80, and the motion image of the object is reduced and displayed on the motion image frame. The display position of the reduced motion image moves by operating cursor keys 86a to 86d after the reduced motion image is displayed, as shown in Fig. 20E. When the operator presses shutter button 89 while the reduced motion image is being displayed on monitor 80, only the image in the motion image frame is recorded on memory card 82 as shown in Fig. 20F.

When the operator sets the mode setting switch 87 to the reproducing side, CPU 83 performs the processing represented by the flow chart of Figs. 14 to 18. First, in step S35, zoom magnification and the frame data are initialized, and in step S37, the pic file is reproduced from memory card 82. In step S37, a read instruction is applied to memory card 82 so that the latest pic file is read, and the compressed image data stored in the pic file are decompressed by compression/decompression circuit 77. When decompression is completed, a write request of decompressed image data is input from compression/decompression circuit 77 to memory control circuit 78. CPU 83 inputs initial frame data to memory control circuit 78

at the same timing as the write request in step S38, so that the decompressed image data is written to video memory area 81a. In this manner, a still image frame corresponding to the monitor frame is formed in video memory area 81a, and the decompressed image data, that is, the reproduced still image data are written to the still image frame.

Thereafter, CPU 83 applies the initial frame data and the read request to memory control circuit 78 in step S39, and reads the reproduced image data from video memory area 81a. Accordingly, the reproduced image is displayed on monitor 80. Thereafter, CPU 83 monitors operation of cursor key 86c or 86d, and monitors whether the motion image reducing mode, a still image cutting mode and a still image paste mode is set or not in steps S45, S47 and S49, respectively. When there is no key operation and no mode setting, CPU 83 repeats the operation of step S39, and accordingly, the same still image is continuously displayed on monitor 80.

When cursor key 86c or 86d is operated, CPU 83 reproduces another pic file from memory card 82 in step S43, and thereafter returns to step S39. In this case also, CPU 83 applies a read instruction to memory card 82 to read a desired pic file, and the compressed image stored in the pic file is decompressed by compression/decompression circuit 77. The decompressed image data are overwritten on video memory area 81a in step S38. Thus the reproduced image to be displayed on monitor 80 is updated. When the motion image reducing mode is selected, the flow proceeds to step S51, when the still image cutting mode is selected, the flow proceeds to step S73, and when the still image paste mode is selected, the flow proceeds to step S88.

When the motion image reducing mode is set, CPU 83 performs the process of determining the motion image frame in accordance with the subroutine shown in Fig. 19 in step S51, and calculates the zoom magnification in accordance with the above equation (3) in step S53. In step S54, the upper left coordinates data, the size data and the zoom magnification are set in zoom circuit 75. Accordingly, a reduced image data corresponding to the size of the motion image frame are output from zoom circuit 75. CPU 83 further sets the frame data of the motion image

frame determined in step 51 and the write request to memory control circuit 78 in step S55, and the reduced image data are written to the motion image frame formed on video memory area 81a. Accordingly, on the reproduced image data which has been already written to the video  
5 memory area 81a, the reduced image data are synthesized. Thereafter, CPU 83 applies the read request and the initial frame data to memory control circuit 78 in step S57, reads all the image data stored in DRAM 81 and outputs the data through monitor 80. When operator operates none of cursor keys 86a to 86d and shutter button 89, CPU 83 repeats the processes  
10 of steps S55 and S57. Consequently, a motion image is displayed on the motion image frame formed on monitor 80, and on a portion of the monitor frame other than the motion image frame, a still image is displayed.

When the operator operates any of cursor keys 86a to 86d, CPU 83 determines that it is "YES" in step S59. In step S61, the same pic file as  
15 the last time is reproduced from memory card 82, the initial frame data is input to memory control circuit 78 in step S62 and the reproduced image data are written to video memory area 81a. In step S63, the upper left X and Y coordinates of the motion image frame are updated, and the flow returns to step S55. In step S55, the reduced image data are written to  
20 the motion image frame of which position has been moved, and in step S57, all the image data in video memory area 81a are read. In this manner, as reproduction of the pic file is repeated every time the cursor keys 86a to 86d is operated, the still image is not missed after the motion image frame is moved.

25 When the operator operates shutter button 89, CPU 83 determines that it is "YES" in step S65, and performs JPEG compression on all the image data stored in video memory area 81a in step S67. At this time, CPU 83 applies the read request and the initial frame data to memory control circuit 78, and applies the compression instruction to  
30 compression/decompression circuit 77. Consequently, compressed image data are generated. Thereafter, in step S68, instruction to form a pic file is applied, and in step S6, instruction to store the compressed image data to the pic file and writing of the frame data of the monitor frame are applied.

Thereafter, in step S71, the pic file in which the compressed image data are stored is stored in memory card 82, and the flow returns to step S35.

When the motion image reducing mode is set with the reproduced image being displayed on monitor 80 as shown in Fig. 21A, a pointer is  
5 displayed on monitor 80 as shown in Fig. 21B. The pointer also moves in accordance with the operation of cursor keys 86a to 86d, and in accordance with the operation of determination key 70, the upper left and lower right coordinates of the motion image frame are determined. When the  
10 determination key is operated at the positions shown in Figs. 21B and 21C, the motion image frame is formed as shown in Fig. 21D, within which the reduced motion image of the object is displayed. The formed motion image frame moves on the screen in accordance with the operation of cursor keys 86a to 86d. As the still image is reproduced repeatedly in accordance with the operation of cursor keys 86a to 86d, the still image which has been  
15 covered by the motion image frame before movement is not missed even when the motion image frame is moved. When the shutter button 89 is pressed after the motion image frame is moved to the position represented by Fig. 21E, all the images displayed are stored in the memory card 82 as shown in Fig. 21F.

Returning to Fig. 14, when it is determined in step S47 that the still image cutting mode is set, CPU 83 processes the subroutine shown in Fig. 19 in step S73 of Fig. 16, and determines the still image frame. In step S75, still image data are read from video memory area 81a, and character data of the still image frame are read from character area 81b and output  
25 to monitor 80. Accordingly, a still image frame is synthesized and displayed on the still image. When the operator operates cursor keys 86a to 86d, CPU 83 determines that it is "YES" in step S77, and updates the upper left coordinate data of the still image frame in step S79. More specifically, the X and Y coordinates of the frame data to be applied to  
30 memory control circuit 78 are updated. Thereafter, the flow returns to step S75. Accordingly, the still image frame moves on monitor 80. When the operator operates shutter button 89, CPU 83 applies the image data in the still image frame to compression/decompression circuit 77 in step S83

and performs JPEG compression thereon. Thereafter, a syn file is formed in step S84, and the compressed image data are stored in the syn file in step S85. In step S87, the syn file storing the compressed image data is stored in memory card 82, and the flow returns to step S35.

5           When the still image cutting mode is set with the still image reproduced from memory card 82 being displayed as shown in Fig. 22A, a pointer is displayed as shown in Fig. 22B. When the cursor keys 86a to 86d and determination key 88 are operated in the similar manner as described above, the upper left and lower right coordinates of the still  
10   image frame are determined. The still image frame is displayed on monitor 80 as shown in Fig. 22D. The still image frame moves in the monitor frame in accordance with the operation of cursor keys 86a to 86d. When shutter button 89 is pressed with the still image frame being displayed as shown in Fig. 22D, only the partial still image within the still  
15   image frame is stored in memory card 82 as shown in Fig. 22E.

          Returning to Fig. 14, if it is determined in step S49 that the still image paste mode is selected, CPU 83 reads any of the syn files from memory card 82 in step S88 shown in Fig. 17, and detects the frame size data of the partial image data stored therein from the header of the syn file.  
20   Further, CPU 83 determines the upper left coordinate of the still image frame such that the partial still image is displayed at the center of the monitor frame, in step S89. When the frame data of the still image frame is determined in this manner, CPU 83 reproduces the same syn file in step S90. More specifically, the same syn file is read from memory card 82, and  
25   the compressed image data contained in the read syn file are decompressed by the compression/decompression circuit 77. Thereafter, the decompressed image data are written to video memory area 81a in step S91. At the time of writing to the video memory area 81a, CPU 83 applies a write request and the frame data determined in steps S88 and S89 to  
30   memory control circuit 78. Accordingly, the still image frame is formed in video memory area 81a, and the decompressed partial still image data are written to the still image frame.

          In step S91, the read request and the initial frame data are applied

to memory control circuit 78, and all the image data in the video memory area 81a are output to monitor 80. Accordingly, on the still image displayed before the setting of the still image paste mode, the still image frame is formed, and the partial still image newly reproduced from memory card 82 is synthesized within the still image frame. When operator operates cursor key 86a or 86b at this time, the partial still image is switched. CPU 83 reproduces the same pic file as the last time in step S94, inputs the initial frame data to memory control circuit 78 in step S95 and writes the reproduced image data to video memory area 81a. In steps S96 and S97, processes similar to those in steps S88 and S89 are performed, and the frame data of the still image frame are updated. Thereafter, another syn file is reproduced in step S97, and the flow returns to step S91. If the partial still image to be reproduced this time is smaller than the partial still image reproduced last time, part of the still image displayed behind the partial still image will be lost. Therefore, the same pic file is reproduced first, and thereafter another syn file is reproduced.

When cursor key 86c or 86d is operated by the operator, the still image displayed behind the partial still image is updated. At this time, CPU 83 determines that it is "YES" in step S99, and another pic file in accordance with the key operation is reproduced in step S100, and the reproduced image data are written to video memory area 81a in step S101. Thereafter, the same syn file is reproduced in step S102 and the flow returns to step S91. In this manner, desired two still images can be selected.

When determination key 88 is pressed with desired two still images being displayed, CPU 83 determines that it is "YES" in step 103, and the flow proceeds to step S105. In step S105, all the image data of video memory area 81a are output to monitor 80 as in step S91. Thereafter, in step S106, whether any of cursor keys 86a to 86d is operated or not is determined and if it is "YES", the upper left coordinates of the frame data to be applied to memory control circuit 78 are updated in step S108. Thereafter, the same pic file as the last time is reproduced in step S109, and the reproduced image data are written to the video memory area 81a in

accordance with the initial frame data in step S110. Thereafter, in step S111, the same syn file as the last time is reproduced in step S111, and the reproduced image data, that is, the partial still image data are written to the still image frame which has been moved, in step S112. In step S112,  
5 the updated frame data and the write request are applied to memory control circuit 78 in the similar manner as described above, and the partial still image data are written to the form still image frame. Thereafter, the flow returns to step S105. In this manner, the display position of the partial still image is changed in accordance with the key operation.

10 When the operator operates the shutter button 89, CPU 83 performs compression processing on all the image data stored in video memory area 81a in step S113, a pic file is formed in step S114, and the compressed image data are stored in the pic file in step S115. Thereafter, the pic file storing the compressed image data is stored in the memory card 82 in step S117, and the flow returns to step S35.

15 When the still image paste mode is set with the still image reproduced from the pic file being displayed on monitor 80, the partial still image reproduced from the syn file is synthesized with the still image of the pic file as shown in Fig. 23B. When cursor key 86a or 86b is operated in  
20 this state, the partial still image is switched, and when cursor key 86c or 86d is operated, the still image behind the partial still image is switched. When the any of cursor keys 86a to 86d is operated after the two images to be synthesized are determined, the partial still image is moved as shown in Fig. 23C. When shutter button 89 is pressed with the partial still image  
25 being arranged at a desired position, all the still images displayed are recorded on memory card 82, as shown in Fig. 23D.

30 Though the reduced motion image is displayed in the motion image frame in the present embodiment, a motion image with the magnification of one (1) may be displayed in the motion image frame. More specifically, only a part of the motion image displayed in the monitor frame in the normal camera mode may be displayed in the motion image frame. In that case, the motion image displayed changes in accordance with the position of the motion image frame.

Further, though the motion image frame and the still image frame are formed to have a rectangle shape in the present embodiment, the motion image frame and the still image frame may be circular. In that case, the size of the frame can be identified by the radius of the circle, and the position of the frame can be specified by the coordinates of the center.

Although the present invention has been described and illustrated in detail, it is clearly understood that the same is by way of illustration and example only and is not to be taken by way of limitation, the spirit and scope of the present invention being limited only by the terms of the appended claims.



WHAT IS CLAIMED IS:

1. A digital camera, comprising:  
image pickup means for picking up an image of an object;  
a monitor for displaying an image;  
first forming means responsive to a motion image frame forming  
5 instruction by an operator for forming a motion image frame smaller than a  
monitor frame on said monitor; and  
motion image display means for displaying a motion image of said  
object picked up by said image pickup means in said motion image frame.
2. The digital camera according to claim 1, wherein  
said first forming means includes  
input means for receiving, as inputs, size information and position  
information of said motion image frame, and  
5 motion image frame forming means for forming said motion image  
frame on said monitor based on said size information and said position  
information.
3. The digital camera according to claim 2, wherein  
said motion image frame is a rectangle, said size information  
includes horizontal size and vertical size of said rectangle, and said position  
information includes vertex coordinates of at least one corner of said  
5 rectangle.
4. The digital camera according to claim 1, wherein  
said motion image display means includes  
zoom processing means for performing reduction zoom processing on  
said motion image based on said monitor frame and said motion image  
5 frame, and  
reduced image display means for displaying a reduced motion image  
reduce by said zoom processing means on said motion image frame.

5. The digital camera according to claim 1, further comprising:  
a recording medium for recording an image; and  
first recording means for recording an image in said motion image  
frame on said recording medium in response to a first recording instruction  
by said operator.

6. The digital camera according to claim 5, wherein  
said first recording means includes  
first file forming means for forming a first image file having a first  
identifier added thereto, and  
first storing means for storing an image in said motion image frame  
in said first image file.

7. The digital camera according to claim 6, wherein said first  
recording means further includes size information writing means for  
writing size information of said motion image frame in said first image file.

8. The digital camera according to claim 1, further comprising:  
a recording medium for recording an image;  
reproducing means responsive to a reproduction instruction by said  
operator for reproducing a still image from said recording medium;  
second forming means responsive to said reproduction instruction for  
forming a still image frame equal to said monitor frame on said monitor;  
and  
still image displaying means for displaying said still image in said  
still image frame.

9. The digital camera according to claim 8, wherein said motion  
image display means includes motion image synthesizing means for  
synthesizing said motion image with said still image based on said motion  
image frame forming instruction.

10. The digital camera according to claim 9, wherein said first

forming means includes motion image frame moving means responsive to a motion image frame moving instruction by said operator for moving said motion image frame.

11. The digital camera according to claim 10, wherein said reproducing means includes same still image reproducing means for reproducing one same said still image in response to said motion image frame moving instruction; and

5        said motion image frame moving means includes position information updating means for updating position information of said motion image frame after said still image is displayed.

12. The digital camera according to claim 9, further comprising second recording means responsive to a second recording instruction by said operator for recording an image in said monitor frame on said recording medium.

13. The digital camera according to claim 12, wherein said second recording means includes

second file forming means for forming a second image file having a second identifier added thereto, and

5        second storing means for storing the image in said monitor frame in said second image file.

14. A digital camera for reproducing a first still image corresponding to a frame monitor from a recording medium and displaying the image on a monitor, comprising:

10        second still image reproducing means responsive to a synthesization instruction from an operator, for reproducing a second still image smaller than said monitor frame from said recording medium; and

synthesizing means for synthesizing said second still image with said first still image.

15. The digital camera according to claim 14, wherein said second still image reproducing means includes

5 detecting means for detecting size of said second still image, and second still image synthesizing means for synthesizing said second still image at the center of said first still image based on a result of detection by said detecting means.

16. The digital camera according to claim 15, further comprising: first changing means responsive to a first changing instruction by said operator for changing said first still image reproduced from said recording medium; and

5 second changing means responsive to a second changing instruction by said operator for changing said second still image reproduced from said recording medium.

17. The digital camera according to claim 16, further comprising moving means responsive to a moving instruction by said operator for moving position of display of said second still image.

18. The digital camera according to claim 17, further comprising recording means responsive to a recording instruction by said operator for recording an image in said monitor frame on said recording medium.

19. The digital camera according to claim 14, wherein said monitor also functions as a view finder.

20. A digital camera having a recording mode for recording a through image of an object picked up through an optical system, a reproducing mode for reproducing the recorded image, and an image synthesizing mode for generating a synthesized image of the through image and the reproduced image, comprising:

image display means for displaying an image;

setting means for setting, in said image synthesizing mode, a

through image display area on a part of a reproduced image displayed by said image display means;

5 images synthesizing means for generating said synthesized image by displaying the through image on the through image display area set by said setting means; and

recording means for recording the synthesized image generated by said image synthesizing means.

21. The digital camera according to claim 20, wherein said setting means includes

5 drawing means for drawing an outer frame of the through image display area of a desired size at a portion of the reproduced image displayed by said image display means, and

position adjusting means for adjusting position of the outer frame of the through image display area drawn by said drawing means.

22. The digital camera according to claim 21, wherein said drawing means changes color of the outer frame when aspect ratio of the outer frame of said through image display area attains a prescribed ratio.

## ABSTRACT OF THE DISCLOSURE

In a digital camera, when a motion image reducing mode is set, a pointer is displayed on a monitor. When the operator operates on cursor key, the pointer moves, and when the operator operates a determination  
5 key at two different pointer positions, a rectangular frame is formed. Namely, the two pointer positions represent upper left and lower right coordinates of the frame. The picked up real time motion image is displayed in the rectangular frame. The displayed motion image is reduced to a magnification corresponding to the ratio of the rectangular  
10 frame with respect to the monitor frame. When the operator operates a shutter button at this time, the image in the motion image frame is recorded on a memory card. As the motion image is displayed in the motion image frame in accordance with the instruction by the operator and the image in the motion image frame is recorded in accordance with the  
15 operation of the shutter button, a processed image can be obtained without the necessity of preparing a separate image processing apparatus.

FIG. 1A





FIG. 1B



20






FIG.3A







FIG.3B




**FIG.4A**




**FIG.4B**




**FIG.5A**



**FIG.5B**



**FIG.5C**



**FIG.5D**




FIG.6A




FIG.6B




FIG.6C




FIG.6D




FIG.6E




FIG.6F




FIG.7




FIG.8




FIG. 9




FIG. 10




FIG.11






FIG. 12




FIG.13




FIG. 14




FIG.15




FIG.16




FIG.17




FIG.18




FIG.19






FIG.20A



FIG.20B




FIG.20C




FIG.20D




FIG.20E




FIG.20F



FIG. 21B

FIG. 21C

FIG. 21D







FIG. 21E

FIG. 21F

FIG. 21G






FIG.22A




FIG.22B




FIG.22C





FIG.22D



FIG.22E




FIG.23A




FIG.23B




FIG.23C





FIG.23D



## Declaration For U.S. Patent Application

As a below named inventor, I hereby declare that:

My residence, post office address and citizenship are as stated below next to my name.

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention **entitled**  
(Insert Title) Digital Camera Capable of Image Processing

the specification of which is attached hereto unless the following is checked:



was filed on \_\_\_\_\_ as United States Application Number or PCT International  
Application Number \_\_\_\_\_ and was amended on \_\_\_\_\_  
(if applicable).

I hereby state that I have reviewed and understand the contents of the above-identified specification, including the claim(s), as amended by any amendment referred to above.

I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations, § 1.56.

I hereby claim foreign priority benefits under Title 35, United States Code, § 119 (a) - (d) of any foreign application(s) for patent or inventor's certificate listed below and have also identified below any foreign application for patent or inventor's certificate having a filing date before that of the application on which priority is claimed:

(List prior  
foreign  
applications.  
See note A  
on back of  
this page)

10-065051(P)	Japan	16/March/1998	Priority Claimed
(Number)	(Country)	(Day/Month/Year Filed)	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No
10-114909(P)	Japan	24/April/1998	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No
(Number)	(Country)	(Day/Month/Year Filed)	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No
10-125089(P)	Japan	07/May/1998	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No
(Number)	(Country)	(Day/Month/Year Filed)	<input type="checkbox"/> Yes <input type="checkbox"/> No
(Number)	(Country)	(Day/Month/Year Filed)	<input type="checkbox"/> Yes <input type="checkbox"/> No

(See note B on back of this page)

☐ See attached list for additional prior foreign applications

I hereby claim the benefit under Title 35, United States Code, § 119(e) of any United States provisional application(s) listed below.

_____ (Application Number)	_____ (Filing Date)
_____ (Application Number)	_____ (Filing Date)

I hereby claim the benefit under Title 35, United States Code, § 120 of any United States application(s) listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States application in the manner provided by the first paragraph of Title 35, United States Code, § 112, I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations, § 1.56 which became available between the filing date of the prior application and the national or PCT international filing date of the application:

(List Prior U.S. Applications)	_____ (Application Serial Number)	_____ (Filing Date)	_____ (Status) (patented, pending, abandoned)
	_____ (Application Serial Number)	_____ (Filing Date)	_____ (Status) (patented, pending, abandoned)

I hereby appoint the following attorney(s) and/or agent(s) to prosecute this application and to transact all business in the Patent and Trademark Office connected therewith:

James E. Armstrong, III, Reg. No. 18,366; William F. Westerman, Reg. No. 29,988; Ken-Ichi Hattori, Reg. No. 32,861; Le-Nhung McLeland, Reg. No. 31,541; Ronald F. Naughton, Reg. No. 24,616; John R. Pegan, Reg. No. 18,069; William G. Kratz, Jr., Reg. No. 22,631; Albert Tockman, Reg. No. 19,722; Mel R. Quintos, Reg. No. 31,898; Donald W. Hanson, Reg. No. 27,133; Stephen G. Adrian, Reg. No. 32,878; William L. Brooks, Reg. No. 34,129; John F. Carney, Reg. No. 20,276; Edward F. Welsh, Reg. No. 22,455; Patrick D. Muir, Reg. No. 37,403; Gay A. Spahn, Reg. No. 34,978; and John P. Kong, Reg. No. 40,054.

Please direct all communications to the following address:

ARMSTRONG, WESTERMAN, HATTORI,  
McLELAND & NAUGHTON  
1725 K Street, N.W., Suite 1000  
Washington, D.C. 20006  
Telephone: (202) 659-2930 Fax: (202) 887-0357

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Title 18 of the United States Code, § 1001 and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

Full name of sole or first inventor (given name, family name) Masahiro SHIOJI

(See note  
C above)

Inventor's Signature Masahiro Shioji Date March 2, 1999

Residence Neyagawa-shi, Osaka, Japan Citizenship Japanese

Post Office Address 25-6, Kotobuki-cho, Neyagawa-shi, Osaka, Japan

Full name of second inventor (given name, family name) Toru ASAEDA

Inventor's Signature Toru Asaeda Date March 2, 1999

Residence Daito-shi, Osaka, Japan Citizenship Japanese

Post Office Address 3-2-5-506, Terakawa, Daito-shi, Osaka, Japan

Full name of third inventor (given name, family name) \_\_\_\_\_

Inventor's Signature \_\_\_\_\_ Date \_\_\_\_\_

Residence \_\_\_\_\_ Citizenship \_\_\_\_\_

Post Office Address \_\_\_\_\_

Full name of fourth inventor (given name, family name) \_\_\_\_\_

Inventor's Signature \_\_\_\_\_ Date \_\_\_\_\_

Residence \_\_\_\_\_ Citizenship \_\_\_\_\_

Post Office Address \_\_\_\_\_

Full name of fifth inventor (given name, family name) \_\_\_\_\_

Inventor's Signature \_\_\_\_\_ Date \_\_\_\_\_

Residence \_\_\_\_\_ Citizenship \_\_\_\_\_

Post Office Address \_\_\_\_\_

Full name of sixth inventor (given name, family name) \_\_\_\_\_

Inventor's Signature \_\_\_\_\_ Date \_\_\_\_\_

Residence \_\_\_\_\_ Citizenship \_\_\_\_\_

Post Office Address \_\_\_\_\_

Full name of seventh inventor (given name, family name) \_\_\_\_\_

Inventor's Signature \_\_\_\_\_ Date \_\_\_\_\_

Residence \_\_\_\_\_ Citizenship \_\_\_\_\_

Post Office Address \_\_\_\_\_

Full name of eighth inventor (given name, family name) \_\_\_\_\_

Inventor's Signature \_\_\_\_\_ Date \_\_\_\_\_

Residence \_\_\_\_\_ Citizenship \_\_\_\_\_

Post Office Address \_\_\_\_\_